# **ELECTRIC STRIKES**

## RIM EXIT & UNIVERSAL CYLINDRICAL STRIKES FOR ACCESS CONTROL


















## PRIMARY APPLICATIONS



RIM EXIT STRIKE

## DESCRIPTION

BEA's Electric Strike portfolio includes Rim Exit and Universal Cylindrical strikes for access control applications.

The Rim Exit strike is designed specifically for rim exit devices. This strike is completely surface mounted, which eliminates the need to cut into the door frame.

The Universal Cylindrical strike provides controlled access and security for egress and ingress applications where code compliance and safety are paramount. This strike is UL 294 listed and has been independently tested for over one million cycles of operation.

## FEATURES & BENEFITS

- Three modular faceplates for the most common door types: hollow metal, aluminum and wood
- Accepts 0.50 inch or 0.625 inch latch projections - a perfect compliment for narrow style aluminum frames
- UL 294 listed Universal Cylindrical strike
- Conventional keeper design promotes even-load distribution in the event of a forced entry
- Reinforced housing reduces twisting on imperfect frames
- UL / ULC listed for up to 1500 lbs of static strength



BEA, Inc. **RIDC Park West** 100 Enterprise Drive Pittsburgh, PA 15275-1213 www.BEAinc.com

Customer Service: 800.523.2462 Technical Support: 800.407.4545

### APPLICATIONS



T E C H N I C	AL SPECIFICA	TIONS	
Mode	Fail Safe		
Voltage	12 VAC / VDC	24 VAC / VDC	11 VAC / 16 VDC
Duty	Intermittent, Continuous	Intermittent, Continuous	Intermittent, Intermittent
Sound	Buzz, Silent	Buzz, Silent	Buzz, Buzz
Amps †	0.30, 0.50	0.64, 0.24	0.35, 0.50
Ohms ‡	22, 22	22, 89	22, 22

10STRIKECU			
Mode	Fail Safe, Fail Secu	ire	
Voltage	12 VDC	24 VDC	12 – 24 VAC
Duty	Continuous	Continuous	Intermittent
Sound	Silent	Silent	Buzz
Amps t	0.375	0.190	0.280 – 0.565
Ohms ‡	37	148	37

Fail Safe – Lock or locking device that remains unlocked on loss of power

Fail Secure – Lock or locking device that remains locked on loss of power. Also known as Non-Fail Safe (NFS) Intermittent Duty – Energized less than 1 minute with duty ratio 1:5

**Continuous Duty** – Energized 1 minute or more

- † Amp ratings are based on maximum current draw at 50 °F and include initial power-up current
- $\boldsymbol{\ddagger}$  Nominal resistance at 77 °F ±7% tolerance

## RELATED PRODUCTS




4007011/5011

10STRIKERE RIM EXIT **ELECTRIC STRIKE** 




10STRIKECU UNIVERSAL CYLINDRICAL **ELECTRIC STRIKE** 


## DIMENSIONAL DRAWINGS



#### **Universal Cylindrical**



A	Default	Min	Max
Inches	13/16"	<sup>45</sup> /64"	31/32"
Millimeters	20.64 mm	17.86 mm	24.61 mm
В	Default	Min	Max
B Inches	Default <sup>21</sup> / <sub>32</sub> "	Min 1/2"	Max <sup>49</sup> / <sub>64</sub> "



www.BEAinc.com © 2018 BEA, Inc. All rights reserved.

**ELECTRIC STRIKES** RIM EXIT & UNIVERSAL CYLINDRICAL STRIKES FOR ACCESS CONTROL



Customer Service: 800.523.2462 Technical Support: 800.407.4545



